


PRODUCT DATA SHEET

LIGHTNING PROTECTION AND EARTHING SYSTEM COMPONENTS

Code: 61 30 120
ed.11/2023
Description: Copper alloy fastener for conductor 95 – 120 mm²
Page 1 of 2

Application

Fastening round or stranded conductor used in air termination system, down conductor system. Suitable for brick, concrete or metallic surfaces.



Classification as per IEC EN 62561

- Metallic.
- With screws.
- Designed to clamp but allow axial movement of the conductor.

Technical characteristics

Material	Copper alloy (Cu-A)
Conductor clamping screw	M18, copper alloy hex socket set screw
Bottom thread	M8
Diameter	25 mm
Withstands (according to IEC EN 62561-4)	Lateral load, 200 N Axial load, 50 N

Installation instructions

Conductor's dimensions	95–120 mm ² (Ø11 – 13 mm)
Compatibility with conductors made of	Al, Cu, Cu/eSn, SSt (Stainless Steel), St/tZn
Tightening torque of conductor	7 Nm
Fixing on brick or concrete wall	Through a head threaded drive pin or wood screw (not included) and a PVC wall plug (not included)
Fixing on metallic surface	Through M8 screw
Spacing between fasteners of air termination conductors	≤1000 mm for solid conductor ¹⁾ . ≤500 mm for stranded conductor ¹⁾ .
Spacing between fasteners of down conductors	≤1000 mm for solid conductor. ≤1000 mm for stranded conductor used for heights ≤20 m. ≤500 mm for stranded conductor for heights ≥20 m.
Before and after of change of direction or clamp or contraction-expansion absorbing component.	≤300 mm.

Testing as per IEC EN 62561

The component has successfully passed the testing requirements of standard IEC EN 62561-4 "Lightning protection system components (LPSC) – Part 4 : Requirements for conductor fasteners".
Test report No **32161** by accredited laboratory as per ISO 17025

Manufacturing Quality Control

Manufacturing quality control according to standard ISO 9001

Country of Origin

Greece

Unit: piece / Package: 100 pieces

See following typical application of the fastener.

¹⁾Where additional mechanical strength is required, e.g snow, strong winds etc, the spacing between the fasteners should be ≤300 mm.

We reserve the right to introduce changes in the component due to technical evolution.

PRODUCT DATA SHEET**LIGHTNING PROTECTION AND EARTHING SYSTEM COMPONENTS****Code: 61 30 120**

ed.11/2023

Description: Copper alloy fastener for conductor 95 – 120 mm²

Page 2 of 2

